



Advanced Linear Charge Management Controller

Features

- Preset 8.4V Charge Voltage with 1% Accuracy
- Programmable Charge Current Up to 0.9A
- Absolute Maximum Input Voltage: 20V
- Wide Input Operation Voltage: 9V ~ 13.5V
- Pre-Charging, the Charge Current is adjustable
- Ideal for Dual-Cell (8.4V)Li-Ion Batteries
- Constant -Current Charging, the Charge Current is adjustable
- Constant-Voltage Charging
- Constant-Current/Constant-Voltage Charging with Temperature Monitoring
- Automatic Recharge
- Double LEDs Charge Status Indication
- Available in SOP-8L Package

Applications

- Charger for Li-Ion Coin Cell Batteries
- Bluetooth Applications
- Portable MP3 Players, Wireless Headsets

Description


The FS4064 is a highly advanced complete constant-current/ constant voltage linear charger for cell lithium-ion batteries. Its package and low external component count make the FS4064 ideally suited for portable applications. The charge current can be programmed externally with a single resistor, which may be programmed up to 0.9A.

FS4064 determines the charge mode by detecting the battery voltage: Pre-charge, constant current charging, constant voltage charging. The charge current of 0pre-charging and constant –current charging is adjustable. The FS4064 is monitored by temperature monitor during the constant-current and constant-voltage charging. There are two LEDs indicate the charge mode.

The FS4064 is available in the SOP-8L package.



Typical Application Circuit




*The charge current $I_{O(REG)} = V_{CS}/R_{SET}$ (V_{CS} is usually 200mV). Note that OFF indicates the LED is turned off.

*The reverse-blocking protection diode is optional. In addition, the reverse-leakage current of the diode should be kept as small as possible.

Condition	LED1	LED2
No-Load	OFF	ON
Battery Charging	ON	OFF
Charge Complete(Done)	OFF	ON
OVP	OFF	OFF

Table1. Charge Status Summary

**Pin Assignment and Description**

TOP VIEW		PIN	NAME	DESCRIPTION
		1	VIN	Positive Input Supply Voltage.
		2	TS	Temperature Sense
		3	CHRG	Open-Drain Charge Status Output
		4	GND	Ground
		5	VOUT	Charge Current Output
		6	NC	No Connect
		7	CS	Charge Current Program
		8	BAT	Battery Connection

Absolute Maximum Ratings (Note 2)

- Input Supply Voltage (VIN) -0.3V ~ 20V
- CS Pin..... -0.3V ~ VIN + 0.3V
- VOUT Pin Current..... 0.9A
- PD.....2W
- Maximum Junction Temperature +150°C
- Operating Ambient Temperature Range (Note 3).....-40°C ~ +85°C
- Storage Temperature Range-65°C ~ +125°C
- Lead Temperature (Soldering, 10 sec).....+265°C

Note 2: Stresses listed as the above “Absolute Maximum Ratings” may cause permanent damage to the device. Exposure to absolute maximum rating conditions for extended periods may remain possibility to affect device reliability.

Note 3: The FS4064 is guaranteed to meet performance specifications from 0°C to 70°C. Specifications over the -40°C to 85°C operating temperature range are assured by design, characterization and correlation with statistical process controls.



Electrical Characteristics

Operating Conditions: $T_A=25^\circ\text{C}$, $R_1=R_2=4.7\text{k}\Omega$, $R_{TS}=10\text{k}\Omega$, $R_{SET}=0.5\Omega$ unless otherwise specified.

SYMBOL	PARAMETER	CONDITIONS	MIN	TYP	MAX	UNITS
V_{IN}	Input Operation Voltage		9		13.5	V
$V_{IN(OVLO)}$	OVLO Threshold	V_{IN} Rising, $V_{BAT}=8\text{V}$		14		V
	OVLO Hysteresis			0.4		V
I_Q	Input Supply Current	Standby Mode(No-Load)		2		mA
		$V_{IN}=12\text{V}$, $R_1=R_2=0$		400		μA
I_{SLEEP}	Sleep Current	Sum of currents into VOUT pin, $V_{IN}=0$		25		μA
$\Delta V_{VIN-VBAT}$	Minimum Voltage difference Threshold	$V_{IN}-V_{BAT}$		600		mV
Battery Voltage Regulation Constant-current Charge						
$V_{O(REG)}$	Output Voltage		8.316	8.4	8.484	V
I_{BAT}	BAT Pin Current	$V_{BAT}=8.4\text{V}$		10		μA
$V_{(CS)}$	Current Regulation Threshold	Voltage at pin CS , relative to V_{IN}	180	200	220	mV
Trickle Charge						
V_{TRIKL}	Trickle Charge Threshold Voltage	$V_{BAT} < V_{TRIKL}$, $R_{SET}=0.5\Omega$.		6.3		V
I_{TRIKL}	Trickle Charge Current	V_{BAT} Rising, $R_{SET}=0.5\Omega$.		60		mA
ΔV_{TRIKL}	Trickle Charge Voltage hysteresis			100		mV
Battery Recharge						
$\Delta V_{(RCH)}$	Recharge Battery Voltage hysteresis	$V_{FLOAT} - V_{RECHRG}$		80		mV
CHRG Pin						
I_{CHRG}	CHRG Bias Current			3		mA
Temperature Sense Comparator						
$V_{TS-COLD}$	TS Pin Threshold Voltage (Cold)	V_{TS} from Low to High		2.4		V
V_{TS-HOT}	TS Pin Threshold Voltage (Hot)	V_{TS} from High to Low		0.5		V
I_{TS}	TS Pin Output Current			-80		μA
Thermal Protection						
T_{SD}	Thermal Shutdown	Temperature Rising		150		$^\circ\text{C}$



Pin Functions

VIN (Pin 1): Positive Input Supply Voltage. It Provides power to the charger VIN and should be bypassed with a 20 μ F capacitor.

TS (Pin 2): Temperature Sense.

CHRG (Pin 3): Charge Status Indication. When the battery is charging, the CHRG pin is pulled low. When the charge cycle is completed, the CHRG pin is pulled high. When no AC is detected, CHRG is forced high impedance.

GND (Pin 4): Ground.

VOUT (Pin 5): Charge Current Output. It provides charge current to the battery and regulates the final float voltage to 8.4V.


NC (Pin 6): No Connect.

CS (Pin 7): Charge Current Program, Charge Current Monitor and Shutdown Pin. The charge current is programmed by connecting a resistor, R_{SET}.

BAT (Pin 8): Battery Connection.



Block Diagram





Application Information

Functional Description

The FS4064 is an advanced 0.9A linear charge controller for dual-cell Li-Ion or Li-Ion applications. Refer to Block Diagram and Operation Flow Chart (Figure 1) in this section.




Figure 1: Operation Flow Chart



Qualification and Precharge

When power is applied, the FS4064 starts a charge-cycle if a battery is already present or when a battery is inserted. Charge qualification is based on battery temperature and voltage.

The FS4064 suspends charge if the battery temperature is outside the V_{TS1} to V_{TS2} range and suspends charge until the battery temperature is within the allowed range. The FS4064 also checks the battery voltage. If the battery voltage is below the pre-charge threshold $V_{(min)}$, the FS4064 uses pre-charge to condition the battery. The conditioning charge rate $I_{(PRECHG)}$ is set at approximately 15% of the regulation current. The conditioning current also minimizes heat dissipation in the external pass-element during the initial stage of charge. See Figure 2 for a typical charge-profile.




Figure 2: Typical Charge Profile

Current Regulation Phase

The FS4064 regulates current while the battery-pack voltage is less than the regulation voltage, $V_{O(REG)}$. The FS4064 monitors charge current at the CS input by the voltage drop across a sense-resistor, R_{SET} , in series with the battery pack. In current sensing configuration, R_{SET} is between the VIN and CS pins, charge-current feedback, applied through pin CS, maintains a voltage of V_{CS} across the current sense resistor. The following formula calculates the value of the Sense resistor:

$$R_{SET} = \frac{V_{CS}}{I_{O(REG)}}$$

Where, $I_{O(REG)}$ is the desired charging current.

Voltage Phase

The voltage regulation feedback is through the BAT pin. This input is tied directly to the positive side of the battery pack. The FS4064 monitors the battery-pack voltage between the BAT and GND pins. The FS4064 is offered 8.4V output voltage.



Charge Termination Recharge

The FS4064 monitors the charging current during the voltage-regulation phase. The FS4064 declares a done condition and terminates charge when the current drops to the charge termination threshold, I_{TERM} . A new charge cycle begins when the battery voltage falls below the V_{RCH} threshold.

Battery Temperature Monitoring

A negative temperature coefficient (NTC) thermistor located close to the battery pack can be used to monitor battery temperature and will not allow charging unless the battery temperature is within an acceptable range.

Connect a 10k thermistor from the TS pin to ground. With the 80 μ A pull-up current source, the hot temperature voltage threshold is 0.5V. For cold temperature, the voltage threshold is set at 2.4V with 80 μ A of pull-up current. The charge cycle begins or resumes once the temperature is within the acceptable range.

Reverse Blocking Protection

The optional reverse-blocking protection diode, depicted in Figure1 provides protection from a faulted or shorted input, or from a reversed-polarity input source. Without the protection diode, a faulted or shorted input would discharge the battery pack through the body diode of the external pass transistor.

If a reverse-protection diode is incorporated in the design, it should be chosen to handle the fast charge current continuously at the maximum ambient temperature. In addition, the reverse-leakage current of the diode should be kept as small as possible.

Selecting Input Capacitor

In most applications, all that is high-frequency decoupling capacitor. The FS4064 works with both regulated and unregulated external dc supplies. If a non-regulated supply is chosen, the supply voltage to the minimum required input voltage at maximum load. If not, more capacitance must be added to the input of the charger.

Selecting Output Capacitor

The FS4064 does not require any output capacitor for loop stability.

In order to maintain good AC stability in constant Voltage mode, a minimum capacitance of 20 μ F is recommended to bypass the BAT pin to GND. This capacitance provides compensation when there is no battery load. In addition, the battery and interconnections appear inductive at high frequencies. These elements are in the control feedback loop during Constant Voltage mode. Therefore, the bypass capacitance may be necessary to compensate for the inductive nature of the battery pack.

Virtually any good quality output filter capacitor can be used, independent of the capacitor's minimum ESR (Effective Series Resistance) value. The actual value of the capacitor and its associated ESR depends on the forward transconductance (g_m) and capacitance of the external pass transistor. A 20 μ F tantalum or aluminum electrolytic capacitor at the output is usually sufficient to ensure stability for up to a 0.9A output current.



PCB Application Suggestions

The temperature characteristic on the sample PCB (Figure3) is showed as follow.






Figure3: an example of layout for the FS4064



Packaging Information

SOP-8L Package Outline Dimension



Symbol	Dimensions In Millimeters		Dimensions In Inches	
	Min	Max	Min	Max
A	1.350	1.750	0.053	0.069
A1	0.100	0.250	0.004	0.010
A2	1.350	1.550	0.053	0.061
b	0.330	0.510	0.013	0.020
c	0.170	0.250	0.006	0.010
D	4.700	5.100	0.185	0.200
E	3.800	4.000	0.150	0.157
E1	5.800	6.200	0.228	0.244
e	1.270(BSC)		0.050(BSC)	
L	0.400	1.270	0.016	0.050
theta	0°	8°	0°	8°

Subject changes without notice.